



LED SPOT LIGHT-SH55
LED SPOT LIGHT

Product Description:

Simple and lightweight lamp body structure, easy to installation and disassembly.

Precise optical design, pure light color, perfect light spot to create excellent lightings.

Integrated high grade LED Driver with stable performance and longer lifespan.

Die-casting aluminum housing is durable, with Black powder spraying on the surface.

5 year warranty

Product Specs:

LEDs Brand & Type	Bridgelux	Driver	External- NOORTEK driver
Number of LEDs	1	Wattage	10W/12W//15W
Color Temperature	3000K/4000K	Input Voltage	220-240V AC
CRI	>90	Input Frequency	50/60HZ
SDCM	<5	Output Voltage	36V
Beam Angel	25°/36°/40°/55°	Output Current	250mA
Luminous Flux	1278Lm/1100 lm/1000 lm/900 lm	Power Factor	>0.5
Life time L70 (hrs)	5 years	Dimmable	/
Optic Material	Stalinite	IP Rating	IP54
Recess Depth (mm)	80MM	Positional Adjustment	Adjustable/FIXED
Overall Diameter (mm)	65MM	Ambient Temperature	-25 °C < TA < 50 °C
Cut Hole(mm)	55mm	Weight (Kg)	/

Product Image:



MODEL	WATTAGE	LIGHT SOURCE	LIGHT OUTPUT	CCT	BEAM ANGLE	IP	DIMENSION
SH55-12W-IP54-A	12W	Bridgelux	1278 lm	3000K/4000K	25/36/40/55	54	Ø65 H 80 mm
SH55-12W-IP54-F	12W	Bridgelux	1278 lm	3000K/4000K	25/36/40/55	54	Ø65 H 80 mm
SH55-10W-IP54-A	10W	Bridgelux	1000 lm	3000K/4000K	25/36/40/55	54	Ø65 H 80 mm
SH55-15W-IP54-F	15W	Bridgelux	1100 lm	3000K/4000K	25/36/40/55	54	Ø90 H 60 mm
SH55-12W-IP54-F	12W	Bridgelux	900 lm	3000K/4000K	25/36/40/55	54	Ø90 H 60 mm

Warranty:

This product has a warranty period of 5 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Fullamps does not accept responsibility for any installation costs associated with the replacement of this product and Fullamps reserves the right to alter specifications without prior notice.

Head office

Mulaz - Salahidin Road
PO Box 1246 Riyadh 11431

Tel: +966 11 4777200
Fax: +966 11 4789469

Western Region Office

Tahliya Street
PO Box 20798 Jeddah 21465

Tel: +966 12 6650388
Fax: +966 12 6633413

Eastern Region Office

King Abdulaziz Street
PO Box 8492 Dammam 31482

Tel: +966 13 8336500
Fax: +966 13 8329055

ContactUs@noortek.com



www.noortek.com